

Installation Instructions

NMP-A

12VDC Josh Adjustable LED Puck Light

READ PRIOR TO ATTEMPTING INSTALLATION
ALWAYS TURN OFF MAIN POWER BEFORE INSTALLATION
INSTALLATION SHOULD BE CARRIED OUT BY YOUR LOCAL ELECTRICIAN

⚠ IMPORTANT - This equipment is intended to be installed only by qualified personnel. The installation must be made in accordance with the current edition of the National Electrical Code and all applicable state and local building codes. The final installation must be approved by the appropriate, qualified electrical/building inspector(s). Improper installation may result in a fire or electrical hazard. Be sure the electrical power to the circuit has been disconnected before installing this electrical system.

⚠ IMPORTANT - Cet équipement est destiné à être installé uniquement par du personnel qualifié. L'installation doit être faite conformément à l'édition actuelle du Code national de l'électricité et à tous les codes de construction locaux et nationaux applicables. L'installation finale doit être approuvée par un ou plusieurs inspecteurs qualifiés en électricité / bâtiment. Une installation incorrecte peut entraîner un incendie ou un risque électrique. Assurez-vous que l'alimentation électrique du circuit a été déconnectée avant d'installer ce système électrique.

⚠ WARNING: Warranty void if factory installed connector is altered or removed, consult factory for assistance.

SURFACE MOUNT INSTALLATION

REQUIRES: [NMPA-6P-24](#) (Ordered Separately)

- Layout the luminaire(s) to determine length to power line interconnect (ordered separately: [NMPA-6P-24](#)). Each luminaire includes a 72" low voltage wire with quick connect, extension cables are available.
 - Mounting surface must be a minimum of 1/2" thick
 - Up to three luminaires may be installed in an enclosed cabinet size: 3.5" x 11.5" x 12"
 - Ensure electrical power is off.
- Determine mounting position and route luminaire wires under the surface mount body. (Figure 1)
Note: Puck light rotates on axis of ball plungers.
 - Place the surface mount body to mounting surface and secure with screws (included). (Figure 2)
Note: Use wire slot furthest away from luminaire for full adjustment.
 - Place puck slots over the ball plungers and insert into place. (Figure 3)
 - Adjust luminaire to desired angle and pull excess wire if needed. (Figure 4)
 - Connect 72" low voltage wires to power line interconnect ([NMPA-6P-24](#)). (Figure 5)
 - Connect power line interconnect to compatible 12VDC LED driver (ordered separately).

