

# Digital Pocket Multi Stem Thermometer

## FUNCTION:

- A: ON/OFF, H/T FUNCTION.
- B: ON/OFF, °F/°C FUNCTION.
- C: ON/OFF, MAX/MIN (°F/°C) MEMORY RECALLING FUNCTION.
- ONE-HOUR AUTO SHUT OFF

## FEATURE :

- 130MM. STAINLESS STEEL SENSOR PROBE
- MAX/MIN (°F/°C) MEMORY RECALLING
- TEMPERATURE UNIT °F/°C SELECTABLE
- DATA HOLD/TEST FUNCTION SELECTABLE
- 1 SEC. NORMAL TEMPERATURE SENSING TIME
- PROTECTIVE PLASTIC SLEEVE WITH CLIP FOR STAINLESS STEEL
- LOW BATTERY INDICATOR

## SPECIFICATION:

- MEASUREMENT RANGE:  -50°C ~ +150°C OR -58°F ~ +302°F  
 -50°C ~ +300°C OR -58°F ~ +572°F
- RESOLUTION : ±0.1° FOR -19.9° ~ +199.9°, OTHERWISE 1°
- ACCURACY  ±1°C IN THE RANGE OF -30°C ~ +150°C  
 ±1.8°F IN THE RANGE OF -22°F ~ +302°F  
 ±1°C IN THE RANGE OF 151°C ~ +250°C, OTHERWISE MORE THAN ±2°C  
 ±1.8°F IN THE RANGE OF 303.8°F ~ +482°F, OTHERWISE MORE THAN ±4°F
- AMBIENT TEMPERATURE FOR PLASTIC CASING: -10°C ~ +50°C OR +14°F ~ +122°F
- BATTERY : 1 X 1.5V "393" SIZE OR EQUIVALENT

## INSTALLATION:

- UNPACK THE THERMOMETER WITH CARE.
- OPEN THE BATTERY DOOR, INSTALL ONE "393" SIZE OR EQUIVALENT BATTERY INTO THE BATTERY COMPARTMENT. THEN CLOSE THE BATTERY DOOR.
- SLIDING PLASTIC SLEEVE. THE THERMOMETER IS NOW READY FOR USE.
- REPLACE NEW BATTERY WHEN THE LOW BATTERY INDICATOR APPEARS ON THE SCREEN.

## OPERATION:

### **"ON/OFF"---FOR POWER SWITCHING**

"°C / °F"---TO SELECT DESIRED TEMPERATURE UNIT.

"HOLD/TEST"--- PRESS ONCE / SLIDE THE SWITCH, "HOLD" FLASH TO RETAIN READING FOR RECORDING.

"MAX / MIN"--- PRESS ONCE TO RECALL MINIMUM TEMPERATURE TESTED. PRESS AGAIN FOR MAXIMUM TEMPERATURE TESTED. TESTING MODE WILL RESTORE AFTER 3 SECONDS.

## PRECAUTIONS:

- TO OBTAIN THE BEST RESULTS, THE PROBE TIP SHOULD BE IMMERSUED AT LEAST 10MM. INTO THE TESTED SUBSTANCE.
- REMOVE THE BATTERY FROM THE BATTERY COMPARTMENT IF THE THERMOMETER WILL NOT BE USED FOR LONG DURATION OF TIME OR DURING STORAGE.
- THE THERMOMETER CANNOT BE USED OR PUT INSIDE ANY OVEN OR MICROWAVE.