


Measures
up to
400AAC

400AAC
Current Clamp
Accessory Head
Model ACH4



Professional-grade
instruments for field service

- Convenient AC current measurement.
- Slide onto "stick" meter.
- Use AHDL1 optional handle for remote testing with most meters
- Read AC amps directly with meter set to mVAC.
- No battery required.



400 AAC Current Clamp Head

Model ACH4

The ACH4 converts AAC to mVAC at a ratio of 1AAC/1mVAC. To display AC amps directly on a DMM, set the meter to mVAC and read the digital display directly. The decimal will be in the correct place on the display so there's no need to move the decimal in your head. The ACH4 snaps onto any Fieldpiece stick-style meter, including the stick meter, DL2 data logger, and electronic handle. Use the AHDL1 accessory handle or ADLS2 deluxe silicone leads to connect to any other DMM with industry standard jacks.


Features

Versatile	<ul style="list-style-type: none"> ■ Works with the Fieldpiece "stick" meter, DL2 data logger, EHDL1 electronic handle, and DMMs with mVDC ranges. ■ Use accessory handle for remote testing or when not using a stick-style meter.
Rugged	<ul style="list-style-type: none"> ■ Rugged mechanical design. ■ Mechanical ACH4 separated from electronics for better in-service dependability.
Easy to use	<ul style="list-style-type: none"> ■ Remote testing with optional AHDL1 handle. ■ Small size fits into tight, hard to reach spaces. ■ New claw shape of clamp makes for easy wire separation.

Specifications

Current range:	1AAC to 400AAC rms
Conversion rate:	1AAC to 1mVAC
Frequency:	50Hz to 60Hz
Operating temperature:	32°F to 122°F
Accuracy (@72°F±8°F, clamp head only, add to DMM accuracy for total accuracy)	$\pm(1.5\% \text{ rdg} + 0.2A)$, 1 to 20 AAC $\pm(2.5\% \text{ rdg} + 0.3A)$, 20 to 100 AAC $\pm(3.5\% \text{ rdg} + 0.5A)$, 100 to 400 AAC
Temperature coefficient:	less than 0.1% per °F
Maximum conductor diameter:	1.18 inches (30mm)

Use it your way



Standalone:
ACH4+EHDL1

Most DMMs:
ACH4 + AHDL1 + DMM

On data logger:
ACH4 + DL2

On stick meter:
ACH4 + HS30



580 West Central Avenue, Suite A
Brea, California 92821
Phone: (714) 257-9060
Fax: (714) 257-9069
www.fieldpiece.com

MADE IN TAIWAN

Model: ACH4

H25-622



8 72641 00002 8

ACH4v30